LIGHTWAVE
LED Light Therapy Topical Light Infusion

Power On & Off and Login Instructions:

Power Up/Boot: First, turn the main power switch on the back of the system has been toggled to the "on" or up position. On some models you will also need to turn on the system using the software "on/off" switch located next to the LCD screen on the top section of the ENVY (if installed). Once this is done, the system will power up and begin to boot automatically. It is normal for the screen to flicker and/or different screens to appear during this process.

Shut down (Turn off) your system:

IMPORTANT: To properly power down or shut off your system you must follow these instructions. Failure to do so may cause software issue or corruption which may cause your system failure (not reboot or receive error).

1. If Logged in, log off to get to the "login" screen.
2. On the login screen press the power button 
3. You will be prompted to do the 1 of the following:
    a. Shutdown
    b. Restart
    c. Cancel
4. Press "Shutdown" and allow 5 seconds for the software to properly turn off.
    NOTE: The screen may flicker and will turn blank during shut down.
5. It is now safe to turn off main power switch on the back of the system.

Login: Below is a general overview and illustrations of what you may see during boot up and Login. This may be helpful if you are not familiar with the equipment or need to trouble shoot the system. Once the system has booted, you will be at the "login" screen. Simply touch the login button and enter your numeric login pin code (default **admin pin code is "1111"** and **standard user is "1234"**). These pin codes can be changed in the "Config" screen.

NOTE: If you run into any error(s) or difficulties during this process, it is recommended that you shut down (turn off) the unit, disconnect the power cord and let it sit for at least 1 minute. After which you can retry the booting procedure again. If you encounter the same issue please contact Lightwave technical support staff at 866.999.6954 for further guidance.